



US008065136B2

(12) **United States Patent**
Hotho et al.

(10) **Patent No.:** **US 8,065,136 B2**
(45) **Date of Patent:** **Nov. 22, 2011**

(54) **MULTI-CHANNEL ENCODER**

(56) **References Cited**

(75) Inventors: **Gerard Herman Hotho**, Eindhoven (NL); **Dirk Jeroen Breebaart**, Eindhoven (NL); **Evgeny Alexandrovitch Verbitskiy**, Eindhoven (NL); **Albertus Cornelis Den Brinker**, Eindhoven (NL)

U.S. PATENT DOCUMENTS
5,890,125 A * 3/1999 Davis et al. 704/501
7,193,538 B2 3/2007 Craven et al.
7,447,317 B2 11/2008 Herre et al.
2004/0049379 A1 3/2004 Thumpudi et al.

(73) Assignee: **Koninklijke Philips Electronics N.V.**, Eindhoven (NL)

FOREIGN PATENT DOCUMENTS
EP 1107232 A2 6/2001
WO 2004008805 A1 1/2004

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

OTHER PUBLICATIONS
Chonavel et al: "Multi-Channel Linear Predictive Coding of Audio Signals"; 4th European Conference on Speech Communication and Technology. Eurospeech '95, Madrid, Spain, Sep. 18-21, 1995, vol. 1. Conf. 4, XP000854655.

(21) Appl. No.: **12/871,183**

* cited by examiner

(22) Filed: **Aug. 30, 2010**

Primary Examiner — Jakieda Jackson

(65) **Prior Publication Data**
US 2011/0040398 A1 Feb. 17, 2011

(57) **ABSTRACT**
In a method of encoding input signals (CH1 to CH3; 400 to 450) in a multi-channel encoder (5; 15) to generate corresponding output data having down-mix output signals (610, 620) together with complementary parametric data (600), the method includes a first step of down-mixing input signals (CH1 to CH3; 400 to 450) to generate the corresponding down-mix output signals (610, 620), and a second step of processing the input signals (CH1 to CH3; 400 to 450) during down-mixing to generate the parametric data (600) complementary to the down-mix output signals (610, 620). Processing of the input signals (CH1 to CH3; 400 to 450) involves including information in the down-mix signals (610, 620) which is useable during subsequent decoding of the down-mix output signals (610, 620) and the parametric data (600) to determine at least some parameter data and thereby enabling representations of the input signals (CH1 to CH3; 400 to 450) to be subsequently regenerated.

Related U.S. Application Data

(62) Division of application No. 10/599,557, filed as application No. PCT/IB2005/051040 on Mar. 25, 2005, now Pat. No. 7,813,513.

Foreign Application Priority Data

Apr. 5, 2004 (EP) 04101405
Jun. 22, 2004 (EP) 04102862


(51) **Int. Cl.**
G10L 11/00 (2006.01)

(52) **U.S. Cl.** **704/200**

(58) **Field of Classification Search** 381/23, 381/22, 17, 18, 19, 1; 704/200, 200.1

See application file for complete search history.

7 Claims, 5 Drawing Sheets






FIG. 1




FIG.2




FIG.3




FIG.4




FIG.5

MULTI-CHANNEL ENCODER

This is a divisional application of U.S. patent application Ser. No. 10/599,557, filed Oct. 2, 2006.

FIELD OF THE INVENTION

The present invention relates to multi-channel encoders, for example multi-channel audio encoders utilizing parametric descriptions of spatial audio. Moreover, the invention also relates to methods of processing signals, for example spatial audio, in such multi-channel encoders. Furthermore, the invention relates to decoders operable to decode signals generated by such multi-channel encoders.

BACKGROUND TO THE INVENTION

Audio recording and reproduction has in recent years progressed from monaural single-channel format to dual-channel stereo format and more recently to multi-channel format, for example five-channel audio format as often used in home movie systems. The introduction of super audio compact disks (SACD) and digital video disc (DVD) data carriers has resulted in such five-channel audio reproduction contemporarily gaining interest. Many users presently own equipment capable of providing five-channel audio playback in their homes; correspondingly, five-channel audio programme content on suitable data carriers is becoming increasingly available, for example the aforementioned SACD and DVD types of data carriers. On account of growing interest in multi-channel programme content, more efficient coding of multi-channel audio programme content is becoming an important issue, for example to provide one or more of enhanced quality, longer playing time and even more channels. Moreover, this growing interest has prompted standardization bodies such as MPEG to appreciate that design of multi-channel encoders is a relevant topic.

Encoders capable of representing spatial audio information such as audio programme content by way of parametric descriptors are known. For example, in a published international PCT patent application no. PCT/IB2003/002858 (WO 2004/008805), encoding of a multi-channel audio signal including at least a first signal component (LF), a second signal component (LR) and a third signal component (RF) is described. This encoding utilizes a method comprising steps of:

- (a) encoding the first and second signal components by using a first parametric encoder for generating a first encoded signal (L) and a first set of encoding parameters (P2);
- (b) encoding the first encoded signal (L) and a further signal (R) by using a second parametric encoder for generating a second encoded signal (T) and a second set of encoding parameters (P1) wherein the further signal (R) is derived from at least the third signal component (RF); and
- (c) representing the multi-channel audio signal at least by a resulting encoded signal (T) derived from at least the second encoded signal (T), the first set of encoding parameters (P2) and the second set of encoding parameters (P1).

Parametric descriptions of audio signals have gained interest in recent years because it has been shown that transmitting quantized parameters describing audio signals requires relative little transmission capacity. These quantized parameters are capable of being received and processed in decoders to regenerate audio signals perceptually not significantly differing from their corresponding original audio signals.

A problem of significant inter-channel interference arises when output from contemporary multi-channel encoders is

subsequently decoded. Such interference is especially noticeable in multi-channel encoders arranged to yield a good stereo image in association with two-channel down-mix. The present invention is arranged to at least partially address this problem, thereby enhancing the quality of corresponding decoded multi-channel audio.

SUMMARY OF THE INVENTION

An object of the present invention is to provide an alternative multi-channel encoder or block that can be used within a multi-channel encoder which is susceptible to generating encoded output data which is subsequently capable of being decoded with reduced inter-channel interference.

According to a first aspect of the present invention, there is provided a multi-channel encoder operable to process input signals conveyed in a plurality of input channels to generate corresponding output data comprising down-mix output signals together with complementary parametric data, the encoder including:

- (a) a down-mixer for down-mixing the input signals to generate the corresponding down-mix output signals; and
- (b) an analyzer for processing the input signals, said analyzer being operable to generate said parametric data complementary to the down-mix output signals, said encoder being operable when generating the down-mix output signals to allow for subsequent decoding of the down-mix output signals for predicting signals of channels processed and then discarded within the encoder.

The invention is of advantage in that the output data from the encoder is susceptible to being decoded with reduced inter-channel interference, namely enabling enhanced subsequent regeneration of the input signals.

Moreover, the amount of data output from the multi-channel encoder required to represent the input signals is also potentially reduced.

Preferably, the encoder is operable to process the input signals on the basis of time/frequency tiles. More preferably, these tiles are defined either before or in the encoder during processing of the input signals.

Preferably, in the encoder, the analyzer is operable to generate at least part of the parametric data ($C_{1,i}$; $C_{2,i}$) by applying an optimization of at least one signal derived from a difference between one or more input signals and an estimation of said one or more input signals which can be generated from output data from the multi-channel encoder. More preferably, the optimization involves minimizing an Euclidean norm.

Preferably, in the encoder, there are N input channels which the analyzer is operable to process to generate for each time/frequency tile the parametric data, the analyzer being operable to output M(N-M) parameters together with M down-mix output signals for representing the input signals in the output data, M and N being integers and M<N. More preferably, in a case of the integer M being equal to two in the encoder, the down-mixer is operable to generate two down-mix output signals which are susceptible to being replayed in two-channel stereophonic apparatus and being coded by a standard stereo coder. Such a characteristic is capable of rendering the encoder and its associated output data backwardly compatible with earlier replay systems, for example stereophonic two-channel replay systems.

According to a second aspect of the invention, there is provided a signal processor for inclusion in a multi-channel encoder according to the first aspect of the invention, the

processor being operable to process data in the multi-channel encoder for generating its down-mix output signals and parametric data.

According to a third aspect of the invention, there is provided a method of encoding input signals in a multi-channel encoder to generate corresponding output data comprising down-mix output signals together with complementary parametric data, the method including steps of:

- (a) providing the input signals to the multi-channel encoder via a plurality (N) of input channels;
- (b) down-mixing the input signals to generate the corresponding (M) down-mix output signals; and
- (c) processing the input signals to generate said parametric data complementary to the down-mix output signals, wherein processing of the input signals in the multi-channel encoder involves determining the parameter data for enabling representations of the input signals to be subsequently regenerated, said down-mix signals allowing for decoding thereof for predicting content of signals of channels processed in the encoder and then discarded therein.

According to a fourth aspect of the invention, there is provided encoded output data generated according to the method of the third aspect of the invention, said output data being stored on a data carrier.

According to a fifth aspect of the invention, there is provided a decoder for decoding output data generated by an encoder according to the first aspect of the invention, the decoder comprising:

- (a) processing means for receiving down-mix output signals together with parametric data from the encoder, the processing means being operable to process the parametric data to determine one or more coefficients or parameters; and
- (b) computing means for calculating an approximate representation of each input signal encoded into the output data using the parameter data and also the one or more coefficients determined in step (a) for further processing to substantially regenerate representations of input signals giving rise to the output data generated by the encoder.

According to a sixth aspect of the invention, there is provided a signal processor for inclusion in a multi-channel decoder according to the fifth aspect of the invention, the signal processor being operable to assist in processing data in association with regenerating representations of input signals.

According to a seventh aspect of the invention, there is provided a method of decoding encoded data in a multi-channel decoder, said data being of a form as generated by a multi-channel encoder according to the first aspect of the invention, the method including steps of:

- (a) processing down-mix output signals together with parametric data present in the encoded data, said processing utilizing the parametric data to determine one or more coefficients or parameters; and
- (b) calculating an approximate representation of each input signal encoded into the encoded data using the parameter data and also the one or more coefficients determined in step (a) for further processing to substantially regenerate representations of input signals giving rise to the encoded data generated by the encoder.

It will be appreciated that features of the invention are susceptible to being combined in any combination without departing from the scope of the invention.

DESCRIPTION OF THE DIAGRAMS

Embodiments of the invention will now be described, by way of example only, with reference to the following diagrams wherein:

FIG. 1 is a schematic block diagram of an embodiment of a multi-channel encoder including therein a coder according to the invention in relation to a first context of the invention; and

FIG. 2 is a schematic block diagram of an embodiment of a decoder according to the invention compatible with the encoder of FIG. 1 in relation to the first context of the invention;

FIG. 3 is a preferred embodiment of the invention wherein the coder is employed within a multi-channel encoder according to the invention in relation to a second context of the invention;

FIG. 4 is an embodiment of a decoder, using the coder of the invention, compatible with the encoder of FIG. 3 in relation to the second context of the invention; and

FIG. 5 is a configuration where a multi-channel encoder and a multi-channel decoder according to the invention are mutually configured with a standard stereo encoder and decoder.

DESCRIPTION OF EMBODIMENTS OF THE INVENTION

The present invention will be described in first and second contexts. In the first context, the invention is concerned with an encoder which is operable process original input signals to generate corresponding encoded output data capable on being subsequently decoded in a decoder to regenerate perceptually more precise representations of the original input signals than hitherto possible. In the second context, the invention is concerned with specific example embodiments of the invention.

The first context will now be considered with regard to FIGS. 1 and 2. In overview, the present invention is concerned with an encoder indicated generally by **5** in FIG. 1. The encoder **5** includes N input channels for receiving corresponding original input signals; for example, the encoder includes three input channels CH1, CH2, CH3 when N=3. The encoder **5** is operable to process the original input signals of the N channels to generate:

- (a) corresponding encoded output signals at M down-mix channel outputs where $M < N$, for example two channel outputs OP1 and OP2 denoted by **610**, **620** respectively when $M=2$; and

- (b) one or more parametric signal outputs, for example a parametric output denoted by **600**.

In order subsequently to most optimally decode in a decoder output signals generated by the encoder **5**, namely with regard to least-squares-errors, it is contemporarily beneficial that Principal Component Analysis (PCA) be employed in the encoder **5** when generating its encoded output signals **600**, **610**, **620**. Processing of these output signals **600**, **610**, **620** for best possible regeneration of signals at a decoder indicated by **10** in FIG. 2 corresponding to the N input signals presented to the encoder **5** is potentially possible if parameters generated by PCA of the encoder **5** are taken into account. Values for PCA parameters in the signals **600**, **610**, **620** are induced by the original input signals themselves and therefore allow no control over down-mixing occurring in the encoder **5**. Such lack of control renders it contemporarily substantially impossible to obtain a satisfactory stereo image quality when PCA is employed in the encoder **5** and its corresponding decoder **10**.

The inventors have appreciated for the present invention that, when a fixed down-mix is employed in conjunction with the aforementioned M down-mix channels in the encoder **5**, a substantially perfect regeneration of the original input signals at the complementary decoder **10** is potentially possible when

these M down-mix channels are extended by way of an additional appropriate set of N-M channels conveying complementary information. Thus, output signals of M down-mix channels generated by a fixed down-mix cannot be used to regenerate substantially perfect representations of original input signals of N channels when information relating to such N-M channels has been at least partially discarded during encoding. However, the inventors have appreciated that these N-M channels can at least partially be predicted when suitable processing is applied to the M down-mix channels, for example to the outputs **610**, **620**.

Thus, an encoder **5** configured according to the invention predicts from the M down-mix channels at least some information corresponding to the N-M channels at a decoder, while at the same time avoiding a need to send certain parameters from the encoder **5** to the decoder **10**. Such prediction makes use of signal redundancy occurring between signals of the N channels as will be described in more detail later. Moreover, the correspondingly compatible decoder **10** reinstates the redundancy when decoding encoded data provided from the encoder **5**.

In order to further elucidate the present invention, an example embodiment of the encoder **5** illustrated in FIG. **1** will be described and then a method of signal processing employed therein will be presented with reference to its mathematical basis.

The example embodiment of the invention pursuant to the aforementioned second context will now be described with reference to FIGS. **3** and **4**.

In FIG. **3**, there is shown a multi-channel encoder indicated generally by **15**. The encoder **15** includes three processing units **20**, **30**, **40** for receiving six input signals denoted by **400** to **450**; the nature of these six input signals will be elucidated later. The three processing units **20**, **30**, **40** are operable to generate the aforementioned N channels **500** to **520** described with reference to the encoder **5**. The encoder **15** also comprises a mixing and parameter extraction unit **180** for receiving processed outputs **500**, **510**, **520** of the processing units **20**, **30**, **40** respectively. Outputs from the extraction unit **180** comprise the aforementioned third parameter set output **600**, and left and right intermediate signals **950**, **960** respectively connected via an inverse transform and OLA unit **360** to generate the aforesaid down-mix outputs **610**, **620** for left and right channels respectively. Parameter output sets **720**, **820**, **920**, **600** and the down-mix outputs **610**, **620** correspond to encoded output data from the encoder **15** suitable for being subsequently communicated to a corresponding compatible decoder whereat the output data is decoded to regenerate representations of one or more of the six input signals **400** to **450**. Alternatively, the down-mix outputs **610** and **620** can be supplied to a standard stereo coder.

The six original input signals denoted by **400** to **450** comprise: a left front audio signal **400**, a left rear audio signal **410**, an effects audio signal **420**, a center audio signal **430**, a rear front audio signal **440** and a right rear audio signal **450**. The effects signal **420** preferably has a bandwidth of substantially 120 Hz for use in simulating rumble, explosion and thunder effects for example. Moreover, the input signals **400**, **410**, **430**, **440**, **450** preferably correspond to 5-channel home movie sound channels.

The processing units **20**, **30**, **40** are preferably implemented in a manner elucidated in published European patent application no. EP 1,107,232 which is hereby incorporated by reference with regard to these units **20**, **30**, **40**.

The processing unit **20** comprises a segment and transform unit **100**, a parameter analysis unit **110**, a parameter to PCA angle unit **120** and a PCA rotation unit **130**. The transform

unit **100** includes transformed left-front and left-rear outputs **700**, **710** respectively coupled to the PCA rotation unit **130** and the parameter analysis unit **110**. A first parameter set output **720** is coupled via the PCA angle unit **120** to the PCA rotation unit **120**. The rotation unit **120** is operable to process the outputs **700**, **710** and the first parameter set output to generate the processed output **500**. Processing within the unit **20** is performed on the basis of time/frequency tiles.

Similarly, the processing unit **30** comprises a segment and transform unit **200**, a parameter analysis unit **210**, a parameter to PCA angle unit **220** and a PCA rotation unit **230**. The transform unit **200** includes transformed left-front and left-rear outputs **800**, **810** respectively coupled to the PCA rotation unit **230** and the parameter analysis unit **210**. A fourth parameter set output **820** is coupled via the PCA angle unit **220** to the PCA rotation unit **220**. The rotation unit **220** is operable to process the outputs **800**, **810** and the fourth parameter set output to generate the processed output **510**. Processing within the unit **30** is also performed on the basis of time/frequency tiles.

Similarly, the processing unit **40** comprises a segment and transform unit **300**, a parameter analysis unit **310**, a parameter to PCA angle unit **320** and a PCA rotation unit **330**. The transform unit **300** includes transformed left-front and left-rear outputs **900**, **910** respectively coupled to the PCA rotation unit **330** and the parameter analysis unit **310**. A second parameter set output **920** is coupled via the PCA angle unit **320** to the PCA rotation unit **320**. The rotation unit **320** is operable to process the outputs **900**, **910** and the second parameter set output to generate the processed output **520**. Processing within the unit **40** is performed on the basis of time/frequency tiles.

The processed outputs **500**, **510**, **520** correspond to left, center and right processed signals respectively. Moreover, the down-mix outputs **610**, **620** are susceptible to being replayed via contemporary two-channel stereo playback apparatus thereby maintaining backward compatibility with earlier stereo sound systems. The third parameter set output **600** includes additional parameter data which can be processed at a decoder, for example the decoder **10** illustrated in FIG. **2**, together with the output parameter sets **720**, **820**, **920** and the down-mix outputs **610**, **620** to regenerate representations of the six input signals **400** to **450**. A manner in which this down-mix occurs to produce the down-mix outputs **610**, **620** and the parameter data at the third parameter set output **600** will next be described.

Referring again to the first context of the invention with regard to FIGS. **1** and **2**, the original input signals of N channels CH1 to CH3, namely $z_1[n]$, $z_2[n]$, . . . , $z_N[n]$, describe discrete time-domain waveforms of the N channels. These signals $z_1[n]$ to $z_N[n]$ are segmented in the three processing units **20**, **30**, **40**, such segmentation using a mutual common segregation, preferably employing temporally overlapping analysis windows. Subsequently, each segment is converted from being in a temporal format to being in a frequency format, namely from the time domain to the frequency domain, by way of applying a suitable transform, for example a Fast Fourier Transform (FFT) or similar equivalent type of transformation. Such format conversion is preferably implemented in computing hardware executing suitable software. Alternatively, the conversion can be implemented using filter-bank structures to obtain time/frequency tiles. Moreover, the conversion results in segmented sub-band representations of the input signals for the channels CH1 to CH3. For convenience, these segmented sub-band representations of the input signals $z_1[n]$ to $z_N[n]$ are denoted by $Z_1[k]$ to $Z_N[k]$ respectively wherein k is a frequency index.

For convenience, we consider two down-mix channels as illustrated for the encoder **15**, although extension to other numbers of down-mix channels is possible. From the original input signals conveyed in N channels CH1 to CH3, the encoder **5** processes the aforesaid sub-band representations $Z_1[k]$ to $Z_N[k]$ to generate two down-mix channels $L_0[k]$ and $R_0[k]$ as provided in Equations 1 and 2 (Eq. 1 and 2):

$$L_0[k] = \sum_{i=1}^N \alpha_i Z_i[k] \quad \text{Eq. 1} \quad 10$$

$$R_0[k] = \sum_{i=1}^N \beta_i Z_i[k] \quad \text{Eq. 2} \quad 15$$

wherein parameters α_i and β_i are preferably set as required for good stereo image in the two down-mix channels $L_0[k]$ and $R_0[k]$. As elucidated in the foregoing, a subsequent decoder, for example the decoder **10** regenerating representations of the original input signals for CH1 to CH3 is only capable of generating substantially perfect representations when the two down-mix channels $L_0[k]$ and $R_0[k]$ are supplemented with an appropriate set of parameters to substantially regenerate the N-2 missing channels. When fixed down-mixing is employed, to some extent, information of the N-2 discarded channels can be predicted from the two down-mix channels $L_0[k]$ and $R_0[k]$, thereby providing a way of enhancing accuracy of regeneration of the aforesaid representation of the original input signals of channels CH1 to CH3 at a corresponding decoder, for example the decoder **10**.

In a situation where information relating to certain of the N channels is discarded in generating the output signals **600**, **610**, **620**, namely the discarded channels are denoted by $C_{0,i}[k]$, these discarded channels can be predicted from the down-mix channels $L_0[k]$ and $R_0[k]$ by applying Equation 3 (Eq. 3):

$$\hat{C}_{0,i}[k] = \hat{C}_{1,L_0}[k] + \hat{C}_{2,R_0}[k] \quad \text{Eq. 3} \quad 40$$

wherein parameters $\hat{C}_{1,i}$ and $\hat{C}_{2,i}$ are selected according to one or more optimization criteria. Preferably, an optimization criterion employed in the encoder **5** is a minimum Euclidean norm of the signal $C_{0,i}[k]$ and its estimation $\hat{C}_{0,i}[k]$. In order to allow for processing according to Equation 3 to be employed in a decoder complementary to the encoder **5**, the parameters $\hat{C}_{1,i}$ and $\hat{C}_{2,i}$ are preferably included in the third parameter set **600** output from the encoder **5**.

The inventors have appreciated that the parameters $\hat{C}_{1,i}$ and $\hat{C}_{2,i}$ in Equation 3 are related to parameters that are generated in the encoder **5** when minimizing the Euclidean norm of the difference of the signal $Z_i[k]$ and an estimation $\hat{Z}_i[k]$ thereof generated at the decoder **10**. The encoder **5** preferably is configured to employ these latter parameters $Z_i[k]$, $\hat{Z}_i[k]$. A square of the Euclidean norm of the difference of the original input signal $Z_i[k]$ is then calculable in the encoder **5** by applying Equation 4 (Eq. 4):

$$\sum_k |Z_i[k] - \hat{Z}_i[k]|^2 \quad \text{Eq. 4} \quad 60$$

$$\text{wherein } \hat{Z}_i[k] = C_{1,Z_i} L_0[k] + C_{2,Z_i} R_0[k] \quad \text{Eq. 5} \quad 65$$

Minimization of Equation 4 is preferably achieved by applying Equations 6 and 7 (Eq. 6 and 7):

$$C_{1,Z_i} = \frac{\langle L_0[k], Z_i[k] \rangle^* \langle R_0[k] \rangle^2 - \langle R_0[k], Z_i[k] \rangle^* \langle L_0[k], R_0[k] \rangle^*}{\|L_0[k]\|^2 \|R_0[k]\|^2 - |\langle L_0[k], R_0[k] \rangle|^2} \quad \text{Eq. 6}$$

$$C_{2,Z_i} = \frac{\langle R_0[k], Z_i[k] \rangle^* \|L_0[k]\| - \langle L_0[k], Z_i[k] \rangle^* \langle L_0[k], R_0[k] \rangle}{\|L_0[k]\|^2 \|R_0[k]\|^2 - |\langle L_0[k], R_0[k] \rangle|^2} \quad \text{Eq. 7}$$

wherein

$$\|A[k]\|^2 = \sum_k |A[k]|^2 \quad \text{Eq. 8}$$

$$\langle A[k], B[k] \rangle = \sum_k A[k] B^*[k] \quad \text{Eq. 9}$$

Thus, for the parameters C_{1,Z_i} and C_{2,Z_i} as calculable from Equations 6 and 7, the following relationships are derivable from Equations 10 to 13 (Eq. 10 to 13) with regard to coefficients α_i and β_i , for example as relevant to Equations 1 and 2 (Eq. 1 and 2):

$$\sum_{i=1}^N \alpha_i C_{1,Z_i} = 1 \quad \text{Eq. 10}$$

$$\sum_{i=1}^N \beta_i C_{2,Z_i} = 1 \quad \text{Eq. 11}$$

$$-\sum_{i=1}^N \beta_i C_{1,Z_i} = 0 \quad \text{Eq. 12}$$

$$-\sum_{i=1}^N \alpha_i C_{2,Z_i} = 0 \quad \text{Eq. 13}$$

Thus, in the encoder **5**, applying processing operations as described by Equations 1 to 13 (Eq. 1 to 13), it is feasible to convert input signals corresponding to N channels, namely the input signals for CH1 to CH3 wherein N=3, with two parameters per channel and two down-mix channels to generate signals for the outputs **610**, **620** and the third parameter set output **600**; the two parameters for the i-th channel are C_{1,Z_i} and C_{2,Z_i} . If the down-mix is fixed for every time/frequency tile, the down-mix is known at the decoder **10**, so that the relations between the parameters are a priori known. If, on the other hand, it is chosen to vary the down-mix, information regarding the actual down-mix has to be sent to the decoder **10**.

In the encoder **5**, the input signals CH1 to CH3 are processed in the channel unit **100**, **200**, **300** to yield a representation of the input signals in time/frequency tiles. Processing operations as depicted by Equations 1 to 13 are repeated for each of these tiles. The signals $L_0[k]$ of all frequency tiles are combined in the encoder **5** and transformed to the time domain to form a signal for the current segment and this signal is at least partially combined with the signal pertaining to at least a preceding segment thereto to generate the encoded output signal **620**. The signals $R_0[k]$ are processed in a similar manner to the signals $L_0[k]$ to generate the encoded output signal **610**.

In summary, the encoder **5**, and similarly the encoder **15** which is a specific example embodiment of the invention, is operable to encode the three input signals CH1 to CH3 as two

down-mixed channels **610**, **620**, namely $l_o[n]$, $r_o[n]$ and $2N-4$ parameters for each time/frequency tile applied when processing the input signals CH1 to CH3.

Complementary to the encoder **5** illustrated in FIG. 1, similarly the encoder **15** illustrated in FIG. 3, is a complementary decoder presented schematically in FIG. 2 and indicated therein generally by **10**. The decoder **10** includes a processing unit **1000** which is operable to receive the down-mix output signals **610**, **620** from the encoder **5** and also the third parameter set output **600** conveying parametric information, for example values for the aforementioned parameters C_{1,Z_i} and C_{2,Z_i} . The decoder **10** is operable to process signals from the outputs **600**, **610**, **620** received thereat to generate decoded output signals **1500**, **1510**, **1520**, which are decoded representations of the input signals CH1, CH2, CH3 respectively.

At the decoder **10**, when receiving the outputs **600**, **610**, **620** from the encoder **5**, for example conveyed by way of a communication network such as the Internet and/or a data carrier such as a digital video disk (DVD) or similar data medium, for each time/frequency tile, the following processing functions are performed:

(a) the coefficients C_{1,Z_i} and C_{2,Z_i} are computed for all N channels using the $2N-4$ coefficients and the four equations, namely information pertaining to Equations 10 to 13, describing relationships between the coefficients; and then
(b) an approximate representation $\hat{Z}_i[k]$ of each input signal $Z_i[k]$ is computed using Equation 14 (Eq. 14):

$$\hat{Z}_i = C_{1,Z_i} L_o[k] + C_{2,Z_i} R_o[k] \quad \text{Eq. 14}$$

wherein $L_o[k]$ and $R_o[k]$ are the signals representing a time/frequency tile of two down-mix channels received at the decoder **10**, namely the outputs **610**, **620** respectively.

A specific example embodiment of the decoder **10** illustrated in FIG. 2 in the first context will now be described with reference to FIG. 4 in the second context. In FIG. 4, there is shown a decoder indicated generally by **18**. The decoder **18** comprises a segment and transform unit **1600** for transforming the aforementioned down-mix outputs **610**, **620** denoted by r_o , l_o to generate corresponding transformed signals **1650**, **1660** denoted by R_o , L_o respectively. Moreover, the decoder **18** also includes a decoding processor **1610** for receiving the signals **600**, **1650**, **1660** and processing them to generate corresponding processed signals **1700**, **1710**, **1720** relating to left-channel (L), center channel (C) and right-channel (R) respectively.

The signal **1700** is coupled directly and also via a decorrelator **1750** as shown to an inverse PCA unit **1800** which is operable to generate two intermediate outputs L_β , L_s which are coupled to an inverse transform and OLA unit **1900**. The inverse transform unit **1900** is operable to process the intermediate outputs L_β , L_s to generate decoder outputs **2000**, **2010** corresponding to the output **1500** in FIG. 2, namely regenerated versions of the input signals **400**, **410**.

Similarly, the signal **1710** is coupled directly and also via a decorrelator **1760** as shown to an inverse PCA unit **1810** which is operable to generate two intermediate outputs C_s , LFE which are coupled to an inverse transform and OLA unit **1910**. The inverse transform unit **1910** is operable to process the intermediate outputs C_s , LFE to generate decoder outputs **2020**, **2030** corresponding to the output **1510** in FIG. 2, namely regenerated versions of the input signals **420**, **430**.

Similarly, the signal **1720** is coupled directly and also via a decorrelator **1770** as shown to an inverse PCA unit **1820** which is operable to generate two intermediate outputs R_β , R_s which are coupled to an inverse transform and OLA unit **1920**. The inverse transform unit **1920** is operable to process

the intermediate outputs R_β , R_s to generate decoder outputs **2040**, **2050** corresponding to the output **1520** in FIG. 2, namely regenerated versions of the input signals **440**, **450**.

The units **1800**, **1810**, **1820** require parameter inputs **920**, **820**, **720** during operation to receive sufficient data for correct operation.

Processing operations executed within the decoding processor **1610**, also known as a decoder according to the invention, involve mathematical operations as described in the foregoing with reference to the decoder **10** illustrated in FIG. 2.

It will be appreciated that embodiments of the invention described in the foregoing are susceptible to being modified without departing from the scope of the invention as defined by the accompanying claims.

For example, the encoder **5**, similarly the encoder **15**, is preferably arranged to function so as to generate a good stereo image in the down-mix outputs by applying Equations 15 and 16 (Eq. 15 and 16) during processing:

$$L_o[k] = L[k] + C_s[k] \quad \text{Eq. 15}$$

$$R_o[k] = R[k] + C_s[k] \quad \text{Eq. 16}$$

In such a situation $N=3$ hence only two parameters per tile, as determined by $2N-4$, need to be transmitted from the encoder **5** to the decoder **10**. Such an arrangement is of advantage in that the two parameters or coefficients C_{1,Z_i} and C_{2,Z_i} are nominally in a similar numerical range such that similar quantization can be applied to them.

Correspondingly; at the decoder **10**, when providing three or more channel playback, there are computed for each tile six parameters, namely $C_{1,L}$, $C_{2,L}$, $C_{1,R}$, $C_{2,R}$, $C_{1,Cs}$ and $C_{2,Cs}$. Such computation is based on two transmitted parameters and information regarding relations between these six parameters.

As an example, the coefficients $C_{1,L}$ and $C_{2,R}$ are transmitted from the encoder **5** to the decoder **10**. The decoder **10** is then capable of deriving other coefficients therefrom by way of Equations 17 (Eqs. 17), namely:

$$\begin{aligned} C_{2,L} &= C_{2,R} - 1 & C_{1,R} &= C_{1,L} - 1 \\ C_{1,Cs} &= 1 - C_{1,L} & C_{2,Cs} &= 1 - C_{2,R} \end{aligned} \quad \text{Eqs. 17}$$

When these six coefficients have been derived for each tile, representations of output signals within the encoder **5**, namely $\hat{L}[k]$, $\hat{R}[k]$ and $\hat{C}_s[k]$, can be regenerated within the decoder **10** by using Equation 18 (Eq. 18) in computations executed within the decoder **10**:

$$\begin{bmatrix} \hat{L}[k] \\ \hat{R}[k] \\ \hat{C}_s[k] \end{bmatrix} = \begin{bmatrix} C_{1,L} L_o[k] + C_{2,L} R_o[k] \\ C_{1,R} L_o[k] + C_{2,R} R_o[k] \\ C_{1,C} L_o[k] + C_{2,C} R_o[k] \end{bmatrix} \quad \text{Eq. 18}$$

These signals $\hat{L}[k]$, $\hat{R}[k]$ and $\hat{C}_s[k]$ are then transformable from the frequency domain to the temporal domain to generate signals **1500** to **1520** for output from the decoder **10** for user appreciation, for example during home movie presentation.

In a most straightforward use of the multi-channel encoders **5**, **15**, a standard stereo coder, namely both encoder and decoder, where $M=2$ is employed between the multi-channel encoder **5**, **15** and the multi-channel decoder **10**, **18** described in the foregoing. In other words, referring to FIGS. 3 and 4, the output signals **610**, **620** of FIG. 3 are directly fed to a standard stereo encoder **3000** and thereafter via a multiplexer

11

3002 as depicted in FIG. 5. Outputs 3005 of the multiplexer 3002 which include parameter data (600; 600, 720, 820, 920) are then subsequently conveyed via a data communication route 3010, for example via a data carrier or communication network, to a demultiplexer 3012 and thereafter to a stereo decoder 3020 complementary to the stereo encoder 3000. Decoded output signals 3030 from the decoder 3020 together with the parameter data (600; 600, 720, 820, 920) from the demultiplexer 3012 are fed to the multi-channel decoder 10, 18. The outputs 3030 of the decoder 3020 are regenerated versions of the output signals 610, 620 from the multi-channel encoders 5, 15. A configuration as depicted in FIG. 5 is an example of a manner in which the multi-channel encoders 5, 15 and multi-channels decoders 10, 18 are susceptible to be mutually interconnected.

In the accompanying claims, numerals and other symbols included within brackets are included to assist understanding of the claims and are not intended to limit the scope of the claims in any way.

Expressions such as “comprise”, “include”, “incorporate”, “contain”, “is” and “have” are to be construed in a non-exclusive manner when interpreting the description and its associated claims, namely construed to allow for other items or components which are not explicitly defined also to be present. Reference to the singular is also to be construed to be a reference to the plural and vice versa.

The invention claimed is:

1. An encoder for encoding an N-channel digital audio signal, where $N > 2$, comprising at least a first left-hand digital audio signal component, a second right-hand digital audio signal component and a third digital audio signal component, the encoder comprising:

a matrixing unit for receiving the first, second and third digital audio signal components and deriving therefrom at least a first composite digital audio signal and a second composite digital audio signal, the first composite digital audio signal being a linear combination of at least the first and third digital audio signal components, and the second composite digital audio signal being a linear combination of at least the second and third digital audio signal components;

a prediction unit for deriving a prediction parameter signal from at least the first and second composite digital audio signals; and

a signal combination unit for combining the first and second composite digital audio signals and the prediction parameter signal into a transmission signal.

2. The encoder as claimed in claim 1, characterized in that the prediction parameter signal allows for generating a prediction of a third composite digital audio signal component from the first and second digital composite audio signals, where the third composite digital audio signal is a linear combination of the first, second and third digital audio signal components.

3. The encoder as claimed in claim 2, characterized in that the signal combination unit generates the transmission signal such that it is devoid of a difference signal, said difference signal representing the difference between the third composite digital audio signal component and the prediction of the third composite digital audio signal component.

4. A decoder for decoding a transmission signal comprising a first and a second composite digital audio signal and a prediction parameter signal into an N-channel digital audio signal, where $N > 2$, the N-channel digital audio signal comprising at least a first left-hand digital audio signal compo-

12

nent, a second right-hand digital audio signal component and a third digital audio signal component, the decoder comprising:

an input unit for receiving the transmission signal;

a demultiplexer unit for deriving the first and second composite digital audio signals and the prediction parameter signal from the transmission signal; and

a dematrixing unit for receiving the first and second composite digital audio signals and deriving therefrom the at least first, second and third digital audio signal components, in response to the prediction parameter signal, wherein the at least first, second and third digital audio signal components being linear combinations of the first and second composite digital audio signals using matrixing coefficients, values of at least some of the matrixing coefficients being controllable by the prediction parameter signal.

5. The decoder as claimed in claim 4, wherein the dematrixing unit comprises:

a first circuit part for generating a third composite digital audio signal from the first and second composite digital audio signals and the prediction parameter signal, the third composite digital audio signal being a linear combination of the first and second composite digital audio signals using first dematrixing coefficients, the values of which are controllable by the prediction parameter signal; and

a second circuit part for generating the at least first, second and third digital audio signal components from the first, second and third composite digital audio signals using second dematrixing coefficients,

wherein the at least first, second and third digital audio signal components are linear combinations of the first, second and third composite digital audio signals, and the second dematrixing coefficients not being dependent on the prediction parameter signal.

6. The decoder as claimed in claim 4, characterized in that the composite digital audio signals are split into sub-signals, one for each of a plurality of frequency bands, the prediction parameter signal also being split into prediction parameter sub signals, one for each of the plurality of frequency bands, wherein the dematrixing unit derives, from corresponding sub-signals of the first and second composite digital audio signals, corresponding sub-signals of the at least first, second and third digital audio signal components, in response to the corresponding prediction parameter sub-signal of the prediction parameter signal, and wherein the decoder further comprises a transform unit to transform the sub-signals of the first, second and third digital audio signals into said digital audio signal components.

7. The decoder as claimed in claim 6, characterized in that the sub-signals are split into consecutive time signals, one for each of consecutive time intervals in the time domain, the prediction parameter sub-signals also being split into prediction parameter sub-signals for each of the consecutive time intervals, the dematrixing unit further deriving, for the consecutive time intervals in a frequency band, from the consecutive time signals of the corresponding sub-signals of the first and second composite digital audio signals in said frequency band, the time signals of the corresponding sub-signals of the at least first, second and third digital audio signal components in said frequency band, in response to the corresponding prediction parameter sub-signals for said consecutive time intervals.